


CATALOG NUMBER: E-MCAFTJ351 FOR ONE 350 WATT, M131 METAL HALIDE PULSE START LAMP


Line Voltage	120/277/347V			
Regulation Line Volts Line Watts	+/-10% +/- 10%			
Frequency	60 Hz			
Circuit Type	CWA			
Power Factor (min)	90%			
Insulation Class	H(180°)			
Min. Ambient Starting Temp.	-20° F or -30° C			
Line Voltage (Volts)		120	277	347
Line Current (Amps)				
Operating		3.40	1.50	1.20
Open Circuit		3.10	1.40	1.10
Starting		1.60	0.70	0.60
Input Watts (W)		400	400	400
Open Circuit Voltage (V)		275	275	275
Drop Out Voltage (V)		60	140	175
UL(1029) Bench Top Rise		D	С	C
Recommended Fuse (Amp	s)	10	5	3
HIGH POTENTIAL TEST (VOLTS)			
1Minute	2000			
2 Seconds	2500			
Open Circuit Voltage Test(v	volts) 250-300			
Short-Circuit Current Test (Amps)			
Secondary Current	3.2 - 3.8			
Input Current (Amps)		1.05 - 1.80	0.42 - 0.78	0.30 -
		1.00	0.70	U.TU



CORE AND COIL


Dimension A (inches)	1.80
Dimension B (inches)	3.50
Weight (Lbs)	12.25
Lead Lengths (inches)	12


CAPACITOR



RATING 22 Mfd \pm 3% 350 VAC MIN Dry Film Capacitor Thermal Plastic Case Max. Case Temp 100° C NO PCB`S

IGNITOR 37-63-AS-6.9-N7 Ballast to Lamp Distance (BTL): 2 feet






MOUNTING CLIP for round case (Furnished as standard with B suffix ballast)

MOUNTING CLIP for round case (Furnished as standard with B suffix ballast)

BRACKET





C-01



Data is based upon tests performed by Industrias Sola Basic in a controlled environment and representative of relative performance. Actual Performance can vary depending on operating conditions. Specifications are subject to change without notice.





SOLA CANADA **IGHTING & POWE**

171 Ambassador Drive Units 8 & 9 Mississauga, ON L5T 2J1

Phone: 905-670-0746 Fax: 905-670-9689

www.solacanada.com